## **Product Description:**

This Sound Choice Pro Audio product fits into the Commercial Series range. The 801M is a dedicated Pre-Amplifier device often referred to as a mixer. It comes in a very convenient 1U rack size making it ideal for small to medium Public Address and Sound Systems. The 801M allows for up to 8 discreet inputs to be mixed to 1 output.



## **Key Features and Benefits:**

- 4 x Balanced XLR Mic inputs, with +48V phantom power, and input volume control
- 3 x dual RCA inputs
- Mic and Aux inputs have seperate volume control on front panel
- 1 x EMC input
- Bass, Treble and Volume Control over Master output
- REC Output via 2 x RCA outputs
- 1U aluminium case
- Comes with a Chime generator offering a prompt tone for paging
- Input priority switches
- T-319 paging microphone connection
- Power On/Off switch
- External 24V power supply as back up

## **System Specifications:**

Mono Inputs (Balanced)	XLR x 4
Stereo Inputs (Unbalanced)	RCA (pair) x 3
EMC Input	1 x TRS
Rec Output (Unbalanced)	RCA (pair) x 1
Master Output (Balanced)	XLR x 1
Mic Input Impedence	2 kΩ
Line Input Impedence	10 kΩ
EQ	Bass ±10dB at 100Hz, Treble ±10dB at 10kHz
LQ	
Frequency Response	20Hz to 20KHz(±1dB)
- <del></del>	<u> </u>
Frequency Response	20Hz to 20KHz(±1dB)
Frequency Response Power Input	20Hz to 20KHz(±1dB) 240V/50Hz
Frequency Response  Power Input  Dimensions (W x D x H)	20Hz to 20KHz(±1dB) 240V/50Hz 484mm x 295mm x 44mm

