

Product Description:

This Sound Choice Pro Audio product fits into the Commercial Series range. The MA360M is a 3 mic 3 line Bluetooth, USB, FM, paging 5 zone 360W mixer amplifier engineered and built for installed commercial sound system applications.



Key Features and Benefits:

- Rated power 360W
- RWP5 Paging Station to suit this mixer amplifier
- Internal music source (MP3 player, FM Tuner and Bluetooth)
- Siren switch
- Pre-announce chime switch
- Graphic equalizer
- All speaker zone output selector
- Preamp Out and In expansion ports AMP-IN/AMP-OUT/LINK-IN/LINK-OUT
- Phoenix speaker output connector for easy installation
- Phantom power and priority control switches
- Telephone paging input connector
- MOH (Music On Hold) output and level control
- 3 AUX RCA inputs with inter-lock to avoid cross talk
- Individual front panel input and master volume controls
- Current limiter, overload, short circuit and thermal protection
- Selectable priority inputs to duck background music when paging
- 3 balanced XLR mic inputs, with phantom power switch
- Constant voltage 100V, and low impedance 4ohm speaker terminals



System Specifications:

Rated Power:	360W
Cooling:	Convection Cooled
Frequency Response (-3dB):	80Hz-17KHz
Signal to Noise Ratio:	>90dB
Graphic Equaliser:	125,250,500,1,2,4,8kHz
Phantom Power:	15VDC
Mains Power:	240V AC 50Hz
Line RCA Connectors:	3
Mic Input Connectors:	3
Net Weight:	7.0Kg
Gross Weight:	8.1Kg
Dimensions (WxDxH):	420 x 320 x 88mm
Packaging Dimensions 1pcs/pack: (WxDxH)	535 x 435 x 190mm